

L3HARRIS 12500-2500-0X

Smart Battery for Handheld Radios

GENERAL	
RT Nomenclature	12500-2500-0X
Compatibility	RF-7850S, RF-7850M, AN/PRC-152A, AN/PRC-163, RF-7800V
Charging Voltage	12.7 V
Output Voltage	7.2 - 12.7 V Operating
Battery Capacity	7 Ah
Maximum Discharge	8.5 A continuous
Total Power	72 Wh

BH7f0036c -0036w 8 0 84 1 scn/GS0 gs/T11 1 Tf1 10/S04e1279390(a)-10scn3 004	

The 12500-2500-0X features SMBus connectivity, providing more accurate battery status and calibration information with other devices including chargers, analyzers and vehicular adapters. The Smart Battery for Handheld Radios also features a non-light-emitting LED display, giving users a quick indication of remaining power without having to put it on an analyzer or charger. The 12500-2500-0X is compatible with Falcon III® radios and is engineered to meet the high-power demands of L3Harris dual-channel handhelds.

